

WHAT'S INCLUDED:

- (1) Ring™ Video Doorbell Pro
- (1) Screwdriver
- (4) Interchangeable Faceplates
- (1) Optional wiring and connectors
- (1) Drill Bit
- (1) Pro Power Kit
- (1) Installation Screws & Anchors
- (1) Quick Setup Guide



SWITCH - REQUEST TO EXIT, (REX)

Features a durable tamper-resistant cover and long-life LED

KEY FEATURES

- 2" x 2" exit button
- 1/8" durable, tamper-resistant extruded aluminum cover
- Spanner head stainless steel machine screws for mounting on standard electrical box discourages unauthorized attempts to remove plate
- Standard extra bright long-life LED
- SPDT micro-switch
- PUSH to exit font size is 5/16" tall
- Available in 12 Vdc or 24 Vac voltage LED (please specify when ordering)

SWITCH - REQUEST TO EXIT, (REX)

The ROFU Request to Exit (REX) Switch features a ¼” durable, tamper-resistant extruded aluminum cover and 2” x 2” exit button. The device is equipped with a long-life extra bright LED light, an SPDT micro-switch, and spanner head stainless steel machine screws for mounting onto a standard electrical box and discouraging unauthorized attempts to remove plate. The push to exit font size is 5/16” tall for readability.

The request to exit switch is available with 12 Vdc or 24 Vac LEDs. Please specify your voltage when ordering.

SPECIFICATIONS

Dimensions	2 x 2
Construction	Aluminum
Vandal-proof	Yes
Volts AC	24
Volts DC	12